

# Application Note

**AN #: 508A**

**DATE: 04- Oct- 00**

**Page 1 of 1**

**PYRAMID MODEL #** 2012 / 2016 / Merlin

**RADIO MODEL:** Midland 70-1526 UHF

**ENGINEER:** W. Carlin / Rev. PW

**APPROVAL INITIALS**

**ENGINEER**

**DEPT. HEAD**

<b>Connections:</b>	<b><i>Pyramid</i></b>	<b><i>Function</i></b>	<b><i>Radio</i></b>
	Black/Shield	Ground	Chassis
	White	Tx Audio Out	J408 Pin 10
	Blue	On-Air Detect	D905 Cathode
	Green	PTT Out	J407 Pin 7
	Red	Switched B+	Switched side of RV301
	Yellow	Rx Audio In	IC241 Pin 9
	Violet	COR	J408 Pin 7 (Ex Mute)
(Optional)	Brown	Audio Mute Out	RV301 Volume high side
(Optional)	Grey	Mic Mute	N/C

<b>2012/Merlin</b>	J1	[In]	Tx audio level	<b>Pyramid</b>	Mobile COR Polarity:	High
<b>Jumpers:</b>	J2	[Out]	Local PTT Loop	<b>Program:</b>	Mobile Type:	Conv.
					On-Air Polarity:	Low
<b>2016</b>	J1	[Out]	Local PTT Loop		I/O Pin 9	Mute
<b>Jumpers:</b>	J2	[In]	Tx audio level			

**Additional Modifications (2012/2016/Merlin):**None

**Additional Modifications (Radio):** None