

mobile/base scanner

UBC800 XLT - www.unidenshop.com
BearTracker™ Mobile Trunking Scanner with GPS Support

- 2500 Dynamically Allocated Channels
- Up to 400 Systems
- 100 System Quick Keys with 10 Channel Group Quick Keys per System
- TrunkTracker III (EDACS®, Motorola®, EF Johnson®)
- Location-Based Scanning
- 100 System Quick Keys
- ARC800 programming software
- Close Call™ RF Capture Technology
- Dangerous Crossing, road and POI Alert



			Band Plan 1		Band Plan 2		Band Plan 3	
	Lower Edge	Upper Edge	Modulation	Step(kHz)	Modulation	Step(kHz)	Modulation	Step(kHz)
1	25,0000	29,9999	FM	5	FM	5	FM	5
2	30,0000	49,9999	FM	12,5	FM	5	FM	6,25
3	50,0000	79,9999	FM	12,5	FM	5	FM	6,25
4	80,0000	82,9999	FM	10	FM	5	FM	6,25
5	83,0000	84,0149	FM	12,5	FM	5	FM	6,25
6	84,0150	87,2999	FM	12,5	FM	20	FM	6,25
7	87,3000	107,9999	FMB	50	FMB	50	FMB	50
8	108,0000	136,9999	AM	12,5	AM	12,5	AM	12,5
9	137,0000	137,9999	FM	5	FM	5	FM	5
10	138,0000	143,9999	FM	12,5	FM	5	FM	6,25
11	144,0000	145,9999	FM	12,5	FM	12,5	FM	6,25
12	146,0000	155,9999	FM	12,5	FM	10	FM	6,25
13	156,0000	157,4374	FM	12,5	FM	12,5	FM	6,25
14	157,4375	157,9999	FM	12,5	FM	12,5	FM	6,25
15	158,0000	160,5999	FM	10	FM	12,5	FM	6,25
16	160,6000	162,0299	FM	12,5	FM	12,5	FM	6,25
17	162,0300	162,5999	FM	12,5	FM	10	FM	6,25
18	162,6000	173,9999	FM	10	FM	10	FM	6,25
19	174,0000	215,9999	WFM	50	WFM	50	WFM	50
20	216,0000	224,9999	FM	5	FM	5	FM	5
21	225,0000	399,9999	AM	25	AM	25	AM	25
22	400,0000	405,9999	FM	12,5	FM	12,5	FM	12,5
23	406,0000	439,9999	FM	6,25	FM	6,25	FM	6,25
24	440,0000	449,9999	FM	5	FM	6,25	FM	6,25
25	450,0000	465,9999	FM	5	FM	10	FM	6,25
26	466,0000	469,9999	FM	10	FM	10	FM	6,25
27	470,0000	512,0000	FM	6,25	FM	6,25	FM	6,25
28	806,0000	960,0000	FM	12,5	FM	12,5	FM	12,5
29	1240,0000	1300,0000	FM	12,5	FM	12,5	FM	12,5